

ELECTRIBE MX / EMX-1 Music Production Sampler Operating System Version 1.02 upgrade instructions.

Before you begin:

Back up all your Pattern and Song data via SmartMedia or MIDI before you update your Operating System! Refer to page 77 (SmartMedia) or page 82 (MIDI) of the EMX-1 Owner's Manual for more information.

And, as always, - never, ever turn off the power while updating your unit.

What you will need:

- 1) A completely blank SmartMedia card, freshly formatted using the EMX-1*
 - 2) A SmartMedia reader/writer attached to your computer*
-

Updating the Operating System:

- 1) In the downloaded folder that contained this document, you will find three Operating System files:

EMX0104F.BFA / EMX0102N.BSA / EMX0100D.BDA

- 2) Copy these three files directly onto the SmartMedia. The files must not be copied while inside of a folder, or placed inside a folder on the SmartMedia. We refer to this as copying to the "root directory". Be sure you copy the files to this root directory level.
-

- 3) Turn off the EMX-1, and set the Master Volume all the way down
- 4) Remove the SmartMedia card from your computer and place it into the EMX-1
- 5) While holding down both the [Cursor up] and [Cursor down] arrow keys, turn the power on.
- 6) When the "SysVerUp...Sure?" message appears in the display, press the blinking START/PAUSE key. (Press the STOP key to cancel).
- 7) The EMX-1 will begin updating the operating system automatically. The 16 step keys will light up in order to show the progress of the update. When the update is complete, the EMX-1 may instruct you to restart the unit.

Enjoy your updated ELECTRIBE MX !